



Motorized Damper (MD) Submittal

This normally closed, power open, 24V or 120V motorized damper for round ducts can be used to control the sequencing of outside air in forced-air systems.



Specifications

Part ID*	Round Duct Size	Frequency (HZ)		Current (Amps)		Power (W)		Insulation Class		Rated Ambient		Noise (dB)	
		24V	120V	24V	120V	24V	120V	24V	120V	24V	120V	24V	120V
MD4	4	50/60		0.3	0.2	6	5	F	40				
MD5	5												
MD6	6												
MD8	8												
MD10	10												
MD12	12												
MD14	14												

UL Recognized Motor

* Standard MD models are 24V, add "-120V" to the part ID for 120V. Ex: MD4-120V

Dimensions

Part ID	Dimensions		
	A	B	C
MD4	1-3/8	9-7/8	4
MD5	1-3/8	9-7/8	5
MD6	1-3/8	9-7/8	6
MD8	1-3/8	9-7/8	8
MD10	1-3/8	9-7/8	10
MD12	1-3/8	11-7/8	12
MD14	2-1/8	14	14

